



PR-410HLF Spec Sheet

Component 1 Size: 4-10" Cast

Voice Coil: 2.5"

Magnet Weight: 56 oz

Component 2 Size: Horn/Driver

Voice Coil: 1"

Magnet Weight: 10 oz

RMS Handling: 600 watts

Program Handling: 1200 watts

Frequency Response (-3dB): 33 – 18 kHz

Useable Low Frequency (-10dB): 29 Hz

Nominal Impedance: 4 ohms

Sensitivity: 96 dB

Maximum SPL: 124 dB

Crossover Frequency: 4 kHz

Dimensions: 30" x 26" x 19"

Weight: 128 lbs